

## F1201.2

F1201.2 offers the potential for use as a full range cabinet, providing balanced low frequency down to 80Hz.

Equally at home as part of a small front of house system or as fills in larger systems, F1201.2 is a versatile tool for both installers and rental users.

An integrated flared bass reflex port minimises turbulence and maximises our refined cabinet tuning. A high resolution 1" HF device and Funktion-One designed waveguide delivers precise high frequencies to 20kHz. F1201.2 benefits from our minimalist approach to passive crossover design, achieving very low distortion and excellent integration between drivers, to give a stable and engaging image. NL4 and Phoenix connector variants are combined into a common connector panel, simplifying purchasing and inventory management.

Combine with BR118 for a powerful, compact mobile system.



### Features:

- Compact enclosure with high output
- High sensitivity/electroacoustic energy efficiency
- Minimalist passive crossover design for maximum resolution
- Dual NL4 and Phoenix connector combination as standard
- Various mounting/rigging options (yoke, wall bracket)
- M8 rigging points
- Integrated 35mm pole mount
- Weather resistant IP55 version available

Frequency Response (-3dB):

55Hz - 20kHz

Weight:

21kg (46.3lbs)

Nominal Dispersion:

90° Horizontal x 60° Vertical

Connectors:

2 x Neutrik NL4 and Phoenix

Driver	Crossover Frequencies	Sensitivity (At 1m)	Power (AES)	Nominal Impedance
12" + 1"	85Hz - Up	100dB at 2.8V	350W	8Ω

\*Measured in free field

Specific crossover settings can be found at [www.funktion-one.com/support](http://www.funktion-one.com/support)

